

16 Way Power Divider



| Model Number | Frequency Range (GHz) | Input VSWR Max | Output VSWR Max | Insertion Loss Max (dB) | Isolation Min (dB) | Amplitude Balance Max (dB) | Phase Balance Max (Deg.) |
|--------------|-----------------------|----------------|-----------------|-------------------------|--------------------|----------------------------|--------------------------|
| D-618-16 | 6.0-18.0 | 1.65:1 | 1.65:1 | 3.60 | 18.0 | 0.80 | 8.0 |
| D-626-16 | 6.0-26.5 | 1.70:1 | 1.70:1 | 4.00 | 16.0 | 0.90 | 9.0 |
| D-640-16 | 6.0-40.0 | 1.80:1 | 1.80:1 | 5.20 | 15.0 | 0.90 | 9.0 |
| D-1026-16 | 10.0-26.5 | 1.70:1 | 1.70:1 | 4.00 | 18.0 | 0.80 | 8.0 |
| D-1040-16 | 10.0-40.0 | 1.80:1 | 1.80:1 | 5.20 | 16.0 | 0.90 | 9.0 |
| D-1826-16 | 18.0-26.5 | 1.70:1 | 1.70:1 | 4.00 | 18.0 | 0.80 | 8.0 |
| D-1840-16 | 18.0-40.0 | 1.80:1 | 1.80:1 | 5.20 | 16.0 | 0.90 | 9.0 |

*For customized frequency range and specifications, please contact a sales representative at sales@etiworld.